











Parallel Connection

Pure **Sinewave**

Eco Mode **Feature**

Oil Warning Indicator

Low Idle / Eco Mode Function

Fuel **Efficient**

Wattmeter **Fuel Gauge**

Low Noise Operation

LCD

Multi-meter

Display


PM6800i

Gasoline Inverter Generator

1 Year Limited Warranty

Carrying Handle





20A



Electrical Aspects

Rated Output: 5500 Watts

Surge Output: 6800 Watts

Phase: Single Phase

Rated Voltage: 230V

Frequency: 60Hz

Rated Current: 23.9A

Pure Sinewave Voltage Regulation: Inverter

Engine: 322cc

Cooling Mode: Air-cooled

4-Stroke. Cylinder: Single Cylinder

Starter: **Electric and Recoil Starter**

Noise Level @ 7m

68 dB(A) and 25% Load:

Unleaded Gasoline Fuel Used:

13.5L **Fuel Capacity:**

Low Oil Alert: Yes

Run Time @ 11 - 5 hrs 50% - 100% Load:

General Specifications

Unit: 695 x 545 x 585 mm **Dimensions (LxWxH):** Packaging: 710 x 560 x 605 mm

Net Weight: 57.5 kg **Gross Weight:** 59 kg

Receptacle: 1 x 5V USB, 1 x Type-C, 2 x AC 230V 20A, 1 x AC 230V 30A Twistlock

Parallel Connection Cable: Not included







