

Promate® 1000 Powerstation

1 Year Limited Warranty
Overcharge Protection

Wireless
Charger



AC/DC
Charging Port



195 Watts Max.
Solar Charging Port



13V DC Socket



13V DC Jack



Digital Display
Battery Status
IN/OUT Wattmeter



1000-Watt
Inverter



Type-C Ports



USB Ports



Specifications

Model:	PROMATE 1000	DC Car Socket:	13V/10A
Battery:	1050Wh 21.9V/48Ah Lithium-ion Battery	DC Jack:	2 x 13V/5A
AC Continuous Power:	1000W Pure Sinewave	Type-C Input/Output:	1 x PD 100W IN/OUT 1 x PD 27W OUT
Input:	DC12V-30V	LED Light:	3 Watts
AC Output:	3 x 220V 60Hz	Wireless Charger:	10 Watts
USB Output:	2 x QC 3.0*2 2 x 5V/2.4A*2	Dimensions (LxWxH):	340 x 236 x 206 mm
		Weight:	11.2 kg

Charging Specifications

AC: 220V AC Inverter (charger included)

DC: Car Cigarette Lighter (charger included)

Solar Panel: DC6530 12V - 30V / 195W Max (solar panel not included)

Sample Usage: (Number of hours based on individual testing)



Around 60 times
Smartphone



Around 20 times
Laptop



Around 30 times
Tablet



Around 10 hrs
LED TV



Around 10 hrs
Projector



Around 8 hrs
Inverter Ref



Around 14 hrs
Electric Fan