Promate

Promate 120 **Powerstation**

1 Year Limited Warranty Overcharge Protection



General Specifications

200 Watts Inverter:

1 x 12 Ah / 12V DC **Battery:** Sealed Lead Acid

Battery Life on

1 hr Full Load:

Solar Charging: 30 Watts

Dimension (LxWxH): 245x163x245mm

Weight: 4.95 kg

Usage & Features

AC Output: 1 x 220V AC Outlet

DC Output: 2 x 12V DC Sockets

3 x 5V Sockets **USB**:

LED Light: 1.5 Watts

AC Voltage, Frequency, **LED Display** Power, Battery

Car Jumper: N/A

Charging Specifications

220V AC Inverter (charger included) AC:

Car Cigarette Lighter (charger included) DC:

Solar Panel: 30 Watts Max (not included)

Sample Usage: (Number of hours based on individual testing)



100 hrs Built-in **LED** light



6 times (via USB) **Smartphone**



3-4 hrs Laptop



2 hrs **LED TV**



Electric Fan









