

Promate[®] 300 Powerstation

1 Year Limited Warranty
Overcharge Protection

Wireless
Charger



AC Adapter &
Car Charger / PV
Inputs



13V DC Socket



DC & Car Outlet
Outputs



Digital Display
Battery Status
IN/OUT Wattmeter



300-Watt
Inverter



USB-A Ports



USB-C Ports



5 LED
Light Modes
(25%, 50%, 100%, SOS, FLASH)

Specifications

Model:	PROMATE 300	AC Outputs:	2 x 230V 60Hz Pure Sinewave
Battery:	265.7Wh 25.55V/10.4Ah Lithium-ion Battery	AC Power Output:	300W Rated 600W Surge
Wireless Charger:	1 x 15W	USB-C Output:	2 x 65W max.
Light Modes:	25%, 50%, 100%, SOS, and FLASH	USB-A Output:	2 x QC 3.0 24W max.
Dimensions (LxWxH) (mm):	230 x 145 x 148	DC (2) & Car Outlet (1) Output:	12V, total 100W max.
Weight:	N.W. 3.5 kg G.W. 3.8 kg	AC Adapter Input:	1 x 12V \approx 10A 120W max.
		Car Charger Input:	1 x 12V 10A 100W max.
		PV Input:	1 x 18V-25V \approx 5A max. 120W max.

Charging Specifications

AC:	220V AC Inverter (charger included)
DC:	Car Cigarette Lighter (charger included)
Solar Panel:	DC6530 12V - 30V / 120W Max (solar panel not included)

Usage time is based on individual load tests and may vary depending on appliance, conditions, and settings.



Around 16.5 times
Smartphone



Around 16 hrs
Laptop



Around 8 times
Tablet



Around 4 hrs
LED TV



Around 4 hrs
Electric Fan