

Promate®



PM2000i

Gasoline Inverter Generator

1 Year Limited Warranty



LCD Digital Display
V | Hz | H

Multifunction Rotary Button
for easy start

Parallel Operation Outlets

5V USB Port
Type-C Port

AC 230V 20A Outlet



Electrical Aspects

Rated Output:	1600 Watts
Surge Output:	2000 Watts
Phase:	Single Phase
Rated Voltage:	230V
Frequency:	60Hz
Rated Current:	7.0 A
Voltage Regulation:	Pure Sinewave Inverter

Engine:

80cc

Cooling Mode:	Air-cooled
Cylinder:	4-Stroke, Single Cylinder
Starter:	Recoil Starter
Noise Level @ 7m and 25% Load:	60 dB(A)
Fuel Used:	Unleaded Gasoline
Fuel Capacity:	3L
Low Oil Alert:	Yes
Run Time @ 50% - 100% Load:	8.5 - 4 hrs

General Specifications

Dimensions (LxWxH):	510 x 335 x 495 mm
Weight:	15.5 kg
Receptacles:	1 x 5V USB, 1 x Type-C, 1 x AC 230V 20A
Parallel Connection Cable:	Included