

Promate®



Parallel Connection



Pure Sinewave



Eco Mode Feature



Fuel Efficient



Low Noise Operation


PM6800i

Gasoline Inverter Generator

1 Year Limited Warranty



Wattmeter
Fuel Gauge
Low Idle / Eco Mode Function
Oil Warning Indicator



Electrical Aspects

Rated Output:	5500 Watts
Surge Output:	6800 Watts
Phase:	Single Phase
Rated Voltage:	230V
Frequency:	60Hz
Rated Current:	23.9A
Voltage Regulation:	Pure Sinewave Inverter

Engine:

322cc

Cooling Mode:	Air-cooled
Cylinder:	4-Stroke, Single Cylinder
Starter:	Electric and Recoil Starter
Noise Level @ 7m and 25% Load:	68 dB(A)
Fuel Used:	Unleaded Gasoline
Fuel Capacity:	13.5L
Low Oil Alert:	Yes
Run Time @ 50% - 100% Load:	11 - 5 hrs

General Specifications

Dimensions (LxWxH):	Unit: 695 x 545 x 585 mm Packaging: 710 x 560 x 605 mm
Net Weight:	57.5 kg
Gross Weight:	59 kg
Receptacles:	1 x 5V USB, 1 x Type-C, 2 x AC 230V 20A, 1 x AC 230V 30A Twistlock
Parallel Connection Cable:	Not included